Room Guard Privacy Controller

The Room Guard Privacy Controller system provides electronic lock control of multiple doors for any room requiring privacy by the occupants. The most common applications are shared ensuites in hospitals and conference rooms with two or more entry doors.

The system allows all doors to be locked and unlocked from any door in the system. Each lock provides a clear visual indication, both inside and outside, which displays the locked/unlocked status of the door at a glance.

Major Features

- 'One touch' privacy
- Clear visual indication (LED)
- Unique integrated turn knobs
- Emergency override
- Made in Australia





ASSA ABLOY, the global leader in door opening solutions

Room Guard Privacy Controller

Connecting More Than Two Locks

The controller is factory configured for connection to two locks, however, up to four locks can be connected. The total load current of the locks must be identified as a larger fuse and power supply may be required. The system may be adapted to control alternative locking devices such as electromagnetic locks and electric strikes.

Applications

- Shared ensuites/toilets.
- Darkroom Studios.
- Sound Studios.
- Conference Rooms.
- Laboratories.
- Any area for which 'one touch' privacy locking is required.

Features & Specifications

- Lock a room at the press of a button. Clear visual indicationred/green (LED).
- Unique integrated turn knobs.
- Emergency override.
- Made in Australia.

April 08487

SEC-BRO-052

www.assaabloyasiapacific.con www.lockweb.com.au

Operation

 In the dormant state, all locks are unlocked and the LEDs are all GREEN.

To Lock the Room

 Close all doors.
Activate one of the integrated turn knobs located on the inside of each lock.
Simultaneously the lever handles on the outside of each door will lock and the LEDs will change to RED.

(The inside lever handles remain free at all times.)

To Unlock the Room

1. Operate the inside lever handle of any lock. All locks will unlock and the LEDs will return to GREEN.

Emergency override buttons may be discreetly located outside the room.

These buttons enable the room to be unlocked from the outside when the room is occupied.

nter				
product Part Number	Description			
RG2PS	Room Guard Privacy Controller plus regulated power supply (12VDC, 1.5AMP).			
RG2	Room Guard Privacy Controller.			
RG3SC	Turn knobs, designed for the integrated assembly with Lockwood electric mortice locks.			
	Other finishes available upon application.			
A typical room with two doors requires the following equipment: 1 x Room Guard Privacy Controller (RG2PS or RG2)				
2 x Room Guard Privacy Controller turn knobs (RG3SC)				
2 x Electric Mortice Locks (3570ELM0SC)				
2 x Power transfer devices (LC8810)				
2 x Exterior door furniture (1822/70SC)				
2 x Interior door furniture (1920/70SC)				
2 x Emergency release push buttons (see note)				
Note: Due to the variety of installation décor, Lockwood does not supply emergency release push buttons. However we recommend a Clipsal				

model 31 architrave mounting plate with model 30MBP push button, or equivalent, available from most electrical wholesalers.

ASSA ABLOY

ASSA ABLOY Sales Offices & Authorised Agents in Asia Pacific

Victoria – Head Office	NSW – Residential	Tasmania	Wellington	Asian Offices
	Telephone (02) 9624 2666		Telephone+64 (0)4 913 4214	ASSA ABLOY – Malaysia
	Facsimile (02) 9620 9340		Facsimile +64 (0)4 913 4213	ASSA ABLOY – Singapore
				ASSA ABLOY – Thailand
Queensland South	New South Wales – Abloy	Auckland – Residential	Security Merchants Australia	ASSA ABLOY – Hong Kong
	Telephone (02) 9882 6066			ASSA ABLOY – Shanghai
				ASSA ABLOY – Beijing
				ASSA ABLOY – Korea
Queensland North	South Australia	Auckland – Sales Office	Security Merchants NZ	ASSA ABLOY – India
Telephone (07) 4779 0177			Telephone +64 (0)9 355 9240	
Facsimile (07) 4775 1480				Contact the Export Departmer Australia for details.
NSW – Commercial	Western Australia	Christchurch – Sales Office	Export Department	
Telephone (02) 8543 3700	Telephone (08) 9227 9588			40 CLE THIS
Facsimile (02) 9531 7944	Facsimile (08) 9227 8913	Eacsimile $+64(0)33794819$	Facsimile +61 (0)3 8574 3789	No. 1